OPzV Series
Energy Storage Battery

OPZV-1500

2Volt

1500ah @10hr 1800ah @100hr

TUBULAR GEL / Valve Regulated / Maintenance Free



AEG OPzV series valve-regulated lead-acid batteries with construction of positive tubular electrodes and gel electrolyte assures it that provides excellent service life and high level of reliability performance. The battery has good cycling properties and charge acceptance ability, can be used in high-low temperature environment. It is ideally suited for use in telecommunications, UPS, emergency systems, and power generation and distribution, energy storage system.



SPECIFICATION


Nominal Voltage			2V						
Nominal Capacity									
10-HR	5-HR	3-HR	1-HR						
to 1.8V	to 1.8V	to 1.75V	to 1.65V						
1500Ah	1275Ah	1188Ah	865Ah						
Approximate Net V	/eight	107	Kgs (235.8 lbs)						
Internal Resistance	(approx.)	9	<0.30 milliohms						
Max. Charging Cur	rent		300A						
Charging voltage		Equalize: 2.35V @25°C(77°F)							
Charging witage		Standby: 2.25	5V @25°C(77°F)						
Terminal			M10-Ф20						
Operating Temp. R	ange	-40°C to 65	-40°C to 65°C(-40°F~149°F)						
Advice Operating T	emp.	15°C~2	15°C~25°C(59°F~77°F)						
Self Discharge									
1 month			98%						
3 month			92%						
6 month			84%						
AEG OPzV series' se	If discharge <3%/mont	h at 25°C(77°F), The stor	age period may up						

AEG OPzV series' self discharge <3%/month at 25°C(77°F), The storage period may up to 6 months at 25°C(77°F) and then a freshening charge is required.


to o months at 25 c(1/ F) and then a nestern	ng charge is required.
Case and cover	A.B.S. UL94-V0 Optional.
Design Life time	20 years




DIMENSIONS (mm/in)











FEATURE

- Very high cycle stability-due to tubular plate design
- 1500+ cycles at 80% DOD
- Maintenance-free regarding water refilling – due to Valve Regulated design and Gel-technology application
- Design according to DIN 40742
- Standard: IEC60896-21/22
- Installation battery racks design and supply (Optional)



CONSTANT CURRENT DISCHARGE (UNIT: A)



CONSTANT POWER DISCHARGE (UNIT: W/CELL)

10m in	15m in	30m in	1hr	2hr	3hr	5hr	6hr	8hr	10hr	F.V Time	10m in	15m in	30m in	1hr	2hr	3hr	5hr	6hr	8hr	10hr
1721	1505	1109	865	565.0	441.5	304.0	257.5	199.0	169.5	1.65	2886	2586	2010	1490.0	980.0	738.8	603.6	510.7	410.7	331.1
1613	1396	1078	825	535.0	418.0	287.5	243.0	191.0	163.5	1.70	2790	2497	1980	1460.0	958.0	722.0	582.1	492.9	396.4	327.1
1543	1364	1020	790	505.0	396.0	272.5	234.0	183.5	157.5	1.75	2659	2408	1920	1420.0	932.0	702.0	567.9	478.6	385.7	315.0
1466	1294	982	750	477.0	375.0	255.0	218.0	176.5	150.0	1.80	2431	2296	1860	1390.0	916.0	696.0	528.6	446.4	371.4	307.5
1384	1224	925	715	452	355.0	244.5	210.5	167.0	142.0	1.85	2200	2161	1711	1310.0	866.3	656.3	482.1	425.0	344.6	290.4

<u>www.aegbatteries.com</u>

Email: info@aegbatteries.com

OPzV Series
Energy Storage Battery

OPZV-1500


2Volt

1500ah @10hr 1800ah @100hr


TUBULAR GEL / Valve Regulated / Maintenance Free









Charging Curve (25°C)




Cycle Life Vs Depth of Discharge



Temperature Vs Battery Capacity




Self Discharge Characteristics



- A Charging is not necessary unless 100% of capacity is required.
- B Charging before use is necessary to help recover full capacity.
- Charging may fail to restore full capacity. Do not let batteries reach this state.

Charging Voltage Vs Temperature



Cycle Use: Apply constant voltage charge 2. 35V at 25° C(77° F). Initial charging current should be set at less than 0.20C Amps. Switch to float charge to avoid overcharging.

Float use: Apply constant voltage charge of 2. 25V at 25°C(77°F).

Temperature Compensation: Charging Voltage for both Cyclic and Standby applications should be regulated in relation to ambient temperature. As temperature rises charging voltage should be reduced to prevent overcharge and increased as temperature falls to avoid undercharge. 3 mV/cell/°C.



- Power Station
- UPS /Data Center
- Telecom
- Energy Storage
- Emergency Power Suppler





www.aegbatteries.com

Email: info@aegbatteries.com